

Balluff / BNS 819-D05-R12-100-10-FD-S90L

Mekanik konum anahtarı

Üretici ürün kodu: BNS00K9

Seri: BNS



Balluff BNS 819-D05-R12-100-10-FD-S90L (BNS00K9), mekanik konum anahtarı. Bağlantı tipi: 1. Switch position: Konnektör; Gövde malzemesi: Aluminium, Anodized; Boyutlar: 120 x 105 x 85 mm.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1. Switch position: Konnektör
Gövde malzemesi	Aluminium, Anodized
Boyutlar	120 x 105 x 85 mm
Anahtarlama konumu sayısı	5x Roller
Sürüm	Snap contact
Çalışma prensibi	1-5. Switch position: Mechanical
Sürekli akım	1-5. Switch position: 5 A
Anma çalışma gerilimi Ue	1-3. Switch position: 6...60 V 4. Switch position: 30 V AC/36 V DC 5. Switch position: 6...60 V
Montaj	Vertical
Yaklaşma yönü	longitudinal, parallel to attachment surface
Yaklaşma hızı	1-5. Switch position: 60 m/min
Anahtarlama konum aralığı	12 mm

Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 819-D05-R12-100-10-FD-S90L

Mechanical multiple position limit switches

Part/model code: BNS00K9

Series: BNS



Balluff BNS 819-D05-R12-100-10-FD-S90L (BNS00K9): mechanical multiple position limit switches. Connection type: 1. Switch position: Connector; Housing material: Aluminium, Anodized; Dimension: 120 x 105 x 85 mm.

TECHNICAL HIGHLIGHTS

Connection type	1. Switch position: Connector
Housing material	Aluminium, Anodized
Dimension	120 x 105 x 85 mm
Number of switching positions	5x Roller
Version	Snap contact
Operating principle	1-5. Switch position: Mechanical
Continuous current	1-5. Switch position: 5 A
Rated operating voltage Ue	1-3. Switch position: 6...60 V 4. Switch position: 30 V AC/36 V DC 5. Switch position: 6...60 V
Installation	Vertical
Approach direction	longitudinal, parallel to attachment surface
Approach speed	1-5. Switch position: 60 m/min
Switch position spacing	12 mm

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.