


Balluff / BNS 819-B06-D12-61-12-55-0761

Mekanik konum anahtarı

Üretici ürün kodu: BNS02C0

Seri: BNS



Balluff BNS 819-B06-D12-61-12-55-0761 (BNS02C0), mekanik konum anahtarı. Bağlantı tipi: 1-6. Switch position: Screw terminal; Gövde malzemesi: Aluminum, Anodized; Boyutlar: 79 x 84 x 77.5 mm.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1-6. Switch position: Screw terminal
Gövde malzemesi	Aluminum, Anodized
Boyutlar	79 x 84 x 77.5 mm
Sürüm	Snap contact
Çalışma prensibi	1-5. Switch position: Inductive 6. Switch position: Mechanical
Algılama aralığı	2 mm
Sürekli akım	1-5. Switch position: 0.2 A 6. Switch position: 6 A
Anma çalışma gerilimi Ue	1-5. Switch position: 24 V DC 6. Switch position: 250 V AC
Montaj	Vertical
Yaklaşma yönü	longitudinal, parallel to attachment surface
Yaklaşma hızı	6. Switch position: 40 m/min
Anahtarlama konum aralığı	12 mm


Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 819-B06-D12-61-12-55-0761

Multiple-position cam switches with mixed connections

Part/model code: BNS02C0

Series: BNS



Balluff BNS 819-B06-D12-61-12-55-0761 (BNS02C0): multiple-position cam switches with mixed connections. Connection type: 1-6. Switch position: Screw terminal; Housing material: Aluminum, Anodized; Dimension: 79 x 84 x 77.5 mm.

TECHNICAL HIGHLIGHTS

Connection type	1-6. Switch position: Screw terminal
Housing material	Aluminum, Anodized
Dimension	79 x 84 x 77.5 mm
Version	Snap contact
Operating principle	1-5. Switch position: Inductive 6. Switch position: Mechanical
Range	2 mm
Continuous current	1-5. Switch position: 0.2 A 6. Switch position: 6 A
Rated operating voltage Ue	1-5. Switch position: 24 V DC 6. Switch position: 250 V AC
Installation	Vertical
Approach direction	longitudinal, parallel to attachment surface
Approach speed	6. Switch position: 40 m/min
Switch position spacing	12 mm

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.