Balluff / BNS 813-D03-D12-100-20-01-FD

Mekanik konum anahtarı

Üretici ürün kodu: BNS00TK

Seri: BNS

Balluff BNS 813-D03-D12-100-20-01-FD (BNS00TK), mekanik konum anahtarı. Bağlantı tipi: 1-3. Switch position: Screw terminal; Gövde malzemesi: Aluminium, Anodized; Boyutlar: 120 x 80 x 83 mm.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1-3. Switch position: Screw terminal
Gövde malzemesi	Aluminium, Anodized
Boyutlar	120 x 80 x 83 mm
Anahtarlama konumu sayısı	3x Chisel
Sürüm	Safety EN 60204-1
Çalışma prensibi	1-3. Switch position: Mechanical
Sürekli akım	1-3. Switch position: 6 A
Anma çalışma gerilimi Ue	1-3. Switch position: 250 V AC
Montaj	Vertical
Yaklaşma yönü	longitudinal, parallel to attachment surface
Yaklaşma hızı	1-3. Switch position: 40 m/min
Anahtarlama konum aralığı	12 mm

Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 813-D03-D12-100-20-01-FD

Mechanical multiple position limit switches with safety switch positions

Part/model code: BNS00TK

Series: BNS

Balluff BNS 813-D03-D12-100-20-01-FD (BNS00TK): mechanical multiple position limit switches with safety switch positions. Connection type: 1-3. Switch position: Screw terminal; Housing material: Aluminium, Anodized; Dimension: 120 x 80 x 83 mm.

TECHNICAL HIGHLIGHTS

Connection type	1-3. Switch position: Screw terminal
Housing material	Aluminium, Anodized
Dimension	120 x 80 x 83 mm
Number of switching positions	3x Chisel
Version	Safety EN 60204-1
Operating principle	1-3. Switch position: Mechanical
Continuous current	1-3. Switch position: 6 A
Rated operating voltage Ue	1-3. Switch position: 250 V AC
Installation	Vertical
Approach direction	longitudinal, parallel to attachment surface
Approach speed	1-3. Switch position: 40 m/min
Switch position spacing	12 mm

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.