

Balluff / BNS 813-B03-L12-72-10-01

Mekanik konum anahtarı

Üretici ürün kodu: BNS022H

Seri: BNS



Balluff BNS 813-B03-L12-72-10-01 (BNS022H), mekanik konum anahtarı. Bağlantı tipi: 1-3. Switch position: Screw terminal; Gövde malzemesi: Aluminium, Anodized; Boyutlar: 84 x 90 x 77 mm.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1-3. Switch position: Screw terminal
Gövde malzemesi	Aluminium, Anodized
Boyutlar	84 x 90 x 77 mm
Anahtarlama konumu sayısı	3x Roller bearing
Sürüm	Safety EN 60204-1
Çalışma prensibi	1-3. Switch position: Mechanical
Sürekli akım	1-3. Switch position: 6 A
Anma çalışma gerilimi Ue	1-3. Switch position: 250 V AC
Montaj	Horizontal
Yaklaşma yönü	Vertical to mounting surface
Yaklaşma hızı	1-3. Switch position: 120 m/min
Anahtarlama konum aralığı	12 mm

Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 813-B03-L12-72-10-01

Mechanical multiple position limit switches with safety switch positions

Part/model code: BNS022H

Series: BNS



Balluff BNS 813-B03-L12-72-10-01 (BNS022H): mechanical multiple position limit switches with safety switch positions. Connection type: 1-3. Switch position: Screw terminal; Housing material: Aluminium, Anodized; Dimension: 84 x 90 x 77 mm.

TECHNICAL HIGHLIGHTS

Connection type	1-3. Switch position: Screw terminal
Housing material	Aluminium, Anodized
Dimension	84 x 90 x 77 mm
Number of switching positions	3x Roller bearing
Version	Safety EN 60204-1
Operating principle	1-3. Switch position: Mechanical
Continuous current	1-3. Switch position: 6 A
Rated operating voltage Ue	1-3. Switch position: 250 V AC
Installation	Horizontal
Approach direction	Vertical to mounting surface
Approach speed	1-3. Switch position: 120 m/min
Switch position spacing	12 mm

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.