Balluff / BNS 813-B05-L12-61-A-12-05

Mekanik konum anahtarı

Üretici ürün kodu: BNS02NH

Seri: BNS



Balluff BNS 813-B05-L12-61-A-12-05 (BNS02NH), mekanik konum anahtarı. Bağlantı tipi: 1-5. Switch position: Screw terminal; Gövde malzemesi: Aluminium, Anodized; Anahtarlama konumu sayısı: 5x Roller bearing.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1-5. Switch position: Screw terminal
Gövde malzemesi	Aluminium, Anodized
Anahtarlama konumu sayısı	5x Roller bearing
Sürüm	Safety EN 60204-1
Çalışma prensibi	1-5. Switch position: Mechanical
Sürekli akım	1-5. Switch position: 6 A
Anma çalışma gerilimi Ue	1-5. Switch position: 250 V AC
Montaj	Vertical
Yaklaşma yönü	longitudinal, parallel to attachment surface
Yaklaşma hızı	1-5. Switch position: 120 m/min
Ortam sıcaklığı	-5...85 °C
IP koruma derecesi	IP67

Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 813-B05-L12-61-A-12-05

Mechanical multiple position limit switches with safety switch positions

Part/model code: BNS02NH

Series: BNS



Balluff BNS 813-B05-L12-61-A-12-05 (BNS02NH): mechanical multiple position limit switches with safety switch positions. Connection type: 1-5. Switch position: Screw terminal; Housing material: Aluminium, Anodized; Number of switching positions: 5x Roller bearing.

TECHNICAL HIGHLIGHTS

Connection type	1-5. Switch position: Screw terminal
Housing material	Aluminium, Anodized
Number of switching positions	5x Roller bearing
Version	Safety EN 60204-1
Operating principle	1-5. Switch position: Mechanical
Continuous current	1-5. Switch position: 6 A
Rated operating voltage Ue	1-5. Switch position: 250 V AC
Installation	Vertical
Approach direction	longitudinal, parallel to attachment surface
Approach speed	1-5. Switch position: 120 m/min
Ambient temperature	-5...85 °C
IP rating	IP67

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.