


Balluff / BNS 819-B04-L12-61-12-3B

Mekanik konum anahtarı

Üretici ürün kodu: BNS02AA

Seri: BNS



Balluff BNS 819-B04-L12-61-12-3B (BNS02AA), mekanik konum anahtarı. Bağlantı tipi: 1-4. Switch position: Screw terminal; Gövde malzemesi: Aluminium, Anodized; Boyutlar: 79 x 60 x 63 mm.

TEKNİK ÖZELLİKLER

Bağlantı tipi	1-4. Switch position: Screw terminal
Gövde malzemesi	Aluminium, Anodized
Boyutlar	79 x 60 x 63 mm
Anahtarlama konumu sayısı	4x Roller bearing
Sürüm	Snap contact
Çalışma prensibi	1-4. Switch position: Mechanical
Sürekli akım	1-4. Switch position: 0.1 A
Anma çalışma gerilimi Ue	1-4. Switch position: 30 V DC
Montaj	Vertical
Yaklaşma yönü	longitudinal, parallel to attachment surface
Yaklaşma hızı	1-4. Switch position: 120 m/min
Anahtarlama konum aralığı	12 mm


Seçili üretici değerleridir; kaynakta belirtilen koşullar ve dipnotlar geçerlidir. Üretici görseli teslim edilen varyanttan farklı olabilir. Automation özeti orijinal dokümantasyonun yerine geçmez.

Balluff / BNS 819-B04-L12-61-12-3B

Mechanical multiple position limit switches

Part/model code: BNS02AA

Series: BNS



Balluff BNS 819-B04-L12-61-12-3B (BNS02AA): mechanical multiple position limit switches. Connection type: 1-4. Switch position: Screw terminal; Housing material: Aluminium, Anodized; Dimension: 79 x 60 x 63 mm.

TECHNICAL HIGHLIGHTS

Connection type	1-4. Switch position: Screw terminal
Housing material	Aluminium, Anodized
Dimension	79 x 60 x 63 mm
Number of switching positions	4x Roller bearing
Version	Snap contact
Operating principle	1-4. Switch position: Mechanical
Continuous current	1-4. Switch position: 0.1 A
Rated operating voltage Ue	1-4. Switch position: 30 V DC
Installation	Vertical
Approach direction	longitudinal, parallel to attachment surface
Approach speed	1-4. Switch position: 120 m/min
Switch position spacing	12 mm

Selected manufacturer values; source conditions and footnotes apply. The manufacturer illustration may differ from the delivered variant. This Automation summary does not replace the original documentation.